

Z-Wave Protocol Implementation Conformance Statement

Indoor Motion Detector

General Information

Product Identifier:	ZMD-107
Brand Name:	Nexa
Product Version:	HW: 1 FW: 1.00:00.05
Z-Wave Certification #:	ZC10-22067098

Product Features

Battery Quantity	1
Battery Type	CR123 3.0V 1700mAh Lithium Battery
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0006
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Indoor Motion Detector

2 / 4 -When the detector is triggered, the unit will send BASIC_SET command which contains a value to the nodes of Group 2.

Supported Command Classes (16):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta Data V4
Manufacturer Specific V2	Notification V4
Powerlevel	Security 0
Security 2	Supervision
Transport Service V2	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic