

## Z-Wave Protocol Implementation Conformance Statement

### Double Switch

#### General Information

<b>Product Identifier:</b>	ZEN30
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 01 FW: 03.00
<b>Z-Wave Certification #:</b>	ZC14-22080126

#### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable LED Inductive (e.g. Motor)
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Loads Controlled</b>	2
<b>Neutral Wire Required</b>	Yes
<b>Switch Type</b>	Decorator Paddle Push
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Double Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xA008
<b>Z-Wave Product Type:</b>	0xA000
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.16.3
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch DT / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

3 / 5

**Supported Command Classes (19):**

Association Group Information (AGI) V3	Association V2
Basic V2	Binary Switch V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multi Channel V4
Multilevel Switch V4	Powerlevel
Security 2	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	