

## Z-Wave Protocol Implementation Conformance Statement

# Venture WISE Window Sensor

### General Information

<b>Product Identifier:</b>	FGDW-002
<b>Brand Name:</b>	Venture WISE
<b>Product Version:</b>	HW: 2 FW: 3.02
<b>Z-Wave Certification #:</b>	ZC10-22127118

### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	ER14250 or CR2
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Sensors</b>	Air Temperature
<b>Supported Notification Types</b>	Access Control Heat Alarm Home Security Power Management

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1000
<b>Z-Wave Product Type:</b>	0x0702
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.09

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Venture WISE Window Sensor

### Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 1            "Lifeline" reports the device status and allows for assigning single device only (main controller by default).
- 2 / 5            "On/Off" is assigned to the device status - contact sensor (sends Basic Set command frames).
- 3 / 5            "Tamper" is assigned to the TMP switch (sends alarm command frames).

**Supported Command Classes (18):**

Application Status	Association Group Info
Association V2	Basic
Battery	Configuration
CRC-16 Encapsulation	Device Reset Locally
Firmware Update Meta Data V4	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Sensor V5
Notification V5	Powerlevel
Security 0	Version V2
Wake Up V2	Z-Wave Plus Info V2

**Controlled Command Classes (2):**

Basic	Notification V5
-------	-----------------