



## Z-Wave Protocol Implementation Conformance Statement

### Double Relay

#### General Information

<b>Product Identifier:</b>	ZEN52 LR
<b>Brand Name:</b>	ZOOZ
<b>Product Version:</b>	HW: 01 FW: 01.50
<b>Z-Wave Certification #:</b>	ZC14-23020193

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Loads Controlled</b>	2
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, US_LR
<b>Z-Wave Product ID:</b>	0x0202
<b>Z-Wave Product Type:</b>	0x0904
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.15.4
<b>Z-Wave Library Type:</b>	Enhanced End Node 232
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch DT / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Double Relay

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

3 / 5

**Supported Command Classes (19):**

- |                              |  |
|------------------------------|--|
| Application Status           | Association Group Information (AGI) V3 |
| Association V2               | Basic V2                               |
| Binary Switch V2             | Central Scene V3                       |
| Configuration V4             | Device Reset Locally                   |
| Firmware Update Meta Data V5 | Indicator V3                           |
| Manufacturer Specific V2     | Multi Channel Association V3           |
| Multi Channel V4             | Powerlevel                             |
| Security 2                   | Supervision                            |
| Transport Service V2         | Version V3                             |
| Z-Wave Plus Info V2          |  |