

## Z-Wave Protocol Implementation Conformance Statement

# Decora Smart Z-Wave™ 800 Series Switch

### General Information

<b>Product Identifier:</b>	ZW15S
<b>Brand Name:</b>	Leviton
<b>Product Version:</b>	HW: 01 FW: 01.01:02.01
<b>Z-Wave Certification #:</b>	ZC14-24010386

### Product Features

<b>Electric Load Type</b>	ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Switch Load Capacity Watts</b>	1500W Incandescent / Halogen
<b>Switch Type</b>	Decorator Paddle Push with Indicator
<b>Z-Wave Scene Type</b>	Scene
<b>Switch Load Capacity Current</b>	15A General Use, 5A LED/CFL/Electronic Ballast, 15A Magnetic Ballast

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Decora Smart Z-Wave™ 800 Series Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	0x0042
<b>Z-Wave Hardware Platform:</b>	ZGM230SA
<b>Z-Wave Development Kit Version:</b>	7.18.8
<b>Z-Wave Library Type:</b>	Enhanced End Node 232
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch DT / Always On End Node

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

3 / 5

**Supported Command Classes (18):**

Association Group Information (AGI) V3	Association V2
Basic V2	Binary Switch V2
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Powerlevel	Scene Activation
Scene Actuator Configuration	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2