

## Z-Wave Protocol Implementation Conformance Statement

### Relay x2 Z-Wave

#### General Information

<b>Product Identifier:</b>	REL-203-Z-01
<b>Brand Name:</b>	Grenton Sp. z o.o.
<b>Product Version:</b>	HW: 01 FW: 01.00
<b>Z-Wave Certification #:</b>	ZC14-24020402

#### Product Features

<b>Switch Load Capacity Current</b>	16A / 265 Vac summary, 16A channel 1, 8A channel 2
<b>Switch Load Capacity Volt-Ampere</b>	265

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	South Africa, UAE, CEPT (Europe), Bahrain, Cyprus, Moldova, Egypt, French Guiana, Georgia, Iraq, Jordan, Kazakstan, Kuwait, Lebanon, Libya, Maldives, Mauritius, Nigeria, Oman, Philippines, Qatar, Saudi Arabia, Turkmenistan, Uzbekistan, Armenia
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.19.2
<b>Z-Wave Library Type:</b>	Enhanced End Node 232
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch DT / Always On End Node

#### Association Group Information

<b>Group # / Max Nodes</b>	<b>Description</b>
----------------------------	--------------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Relay x2 Z-Wave

2 / 5

3 / 5

### Supported Command Classes (20):

Association Group Information (AGI) V3

Basic V2

Central Scene V3

Device Reset Locally

Indicator V3

Multi Channel Association V3

Multilevel Sensor V11

Security 0

Supervision

Version V3

Association V2

Binary Switch V2

Configuration V4

Firmware Update Meta Data V5

Manufacturer Specific V2

Multi Channel V4

Powerlevel

Security 2

Transport Service V2

Z-Wave Plus Info V2