



## Z-Wave Protocol Implementation Conformance Statement

# Plug-in Dimmer Outlet

### General Information

<b>Product Identifier:</b>	ZW39M(MP31ZD)
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 01 FW: 01.00
<b>Z-Wave Certification #:</b>	ZC14-24070457

### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable LED Incandescent
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Switch Load Capacity Watts</b>	150
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Dimmer Outlet

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xFF0D
<b>Z-Wave Product Type:</b>	0xFF00
<b>Z-Wave Hardware Platform:</b>	EFR32ZG23A
<b>Z-Wave Development Kit Version:</b>	7.19.3
<b>Z-Wave Library Type:</b>	Enhanced End Node 232
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch DT / Always On End Node

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

**Supported Command Classes (16):**

Association Group Information (AGI) V3	Association V2
Basic V2	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Multilevel Switch V4
Powerlevel	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2