


The name of each part



Button

1. Include to network
 - A. Press Button switch 3 times in a row to link device to Z-Wave network or remove device from Z-Wave network.
 - B. Press Button switch 3 times in a row again to cancel to link device to Z-Wave network.
2. Exclude from network
 - A. Acknowledge of Green LED Lightning
 - B. Press Button switch 3 times in a row to link device to Z-Wave network or remove device from Z-Wave network
3. Initialization
 - A. Press Fn switch over 2 minutes to initialize connecting network information.

Fn Display

1. Green LED On : Link to Z-Wave Network
2. Green/Red LED Off : Remove link from Z-Wave Network
3. Green LED blinking : start link to Z-Wave network
4. Red LED blinking : remove the link from Z-Wave network
5. Green LED blinking 10times : Initialize network information

Safety Precaution

- A. Do not disassemble, repair and refurbish.
- B. Do not touch the device with wet hand.

Protocol

1. Role Type : AOS (Always On Slave)
2. Device Type : Repeater
 - A. Generic: GENERIC_TYPE_REPEATER_SLAVE
 - B. Specific: SPECIFIC_TYPE_REPEATER_SLAVE
3. Node Info List

Command Class	Version
COMMAND_CLASS_ZWAVEPLUS_INFO	ZWAVEPLUS_INFO_VERSION_V2
COMMAND_CLASS_VERSION	VERSION_VERSION_V2
COMMAND_CLASS_MANUFACTURER_SPECIFIC	MANUFACTURER_SPECIFIC_VERSION_V2
COMMAND_CLASS_DEVICE_RESET_LOCALLY	DEVICE_RESET_LOCALLY_VERSION_V1
COMMAND_CLASS_POWERLEVEL	POWERLEVEL_VERSION_V1
COMMAND_CLASS_ASSOCIATION	ASSOCIATION_VERSION_V2
COMMAND_CLASS_ASSOCIATION_GRP_INFO	ASSOCIATION_GRP_INFO_VERSION_V2
COMMAND_CLASS_FIRMWARE_UPDATE_MD_V2	FIRMWARE_UPDATE_MD_VERSION_V2

4. Associations
 - Press button on device and report reset information to Group1 (Lifeline)

Group	Name	Nodes	Send mode	Send Commands
Group1	Lifeline	1~5	Single Cast	Reset locally command

Certification

This product can be included and operated in any Z-Wave network with other Z-Wave certified devices from other manufacturers and/or other applications. All non-battery operated nodes within the network will act as repeaters regardless of vendor to increase reliability of the network.