

Z-Wave Protocol Implementation Conformance Statement

Secure Smart Plug 302

General Information

Product Identifier:	SSP 302 ANZ
Brand Name:	Secure Controls
Product Version:	02
Z-Wave Certification #:	ZC10-15030012

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0002
Z-Wave Product Type:	0x0011
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.02
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 4	Z-Wave Plus Lifeline. In this group Energy (Active Energy, Apparent Energy) , Switch Status data will be reported base on the delta or time interval configuration.
2 / 4	Power, In this group Active Power data will be reported base on the delta or time interval configuration.
3 / 4	Electrical Parameter, In this group Voltage, Current and Power Factor data will be reported base on the delta or time interval configuration.
4 / 4	Relay Status, In this group Switch Status data will be reported base on the delta or time interval configuration.
5 / 1	Time, In this device will sync the time and date from the time master in the network.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Secure Smart Plug 302

Controlled Command Classes (1):

Time