

Z-Wave Protocol Implementation Conformance Statement

Home Energy Meter Gen5

General Information

| | |
|--------------------------------|-----------------|
| Product Identifier: | ZW095-A |
| Brand Name: | Aeotec |
| Product Version: | HW: 95 FW: 1.33 |
| Z-Wave Certification #: | ZC10-15040002 |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|------------------------------------|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x005F |
| Z-Wave Product Type: | 0x0102 |
| Z-Wave Hardware Platform: | ZM5202 |
| Z-Wave Development Kit Version: | 6.51.02 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Sub Energy Meter / Always On Slave |

Association Group Information

| Group # / Max Nodes | Description |
|---------------------|---|
| 1 / 5 | Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. Automatic Reports will be sent to the associated nodes in association group 1. |