



## Z-Wave Protocol Implementation Conformance Statement

# HomeSeer HS3 Home Automation Software

### General Information

**Product Identifier:** S-HS3  
**Brand Name:** HomeSeer  
**Product Version:**  
**Z-Wave Certification #:** ZC10-15050005

### Product Features

|   |  |
|---|--|
| <b>Supported Meter Type</b>                           | Electric Energy<br>Gas<br>Water  |
| <b>Z-Wave Scene Type</b>                              | Scene & Central Scene  |
| <b>Supported Notification Types</b>                   | Access Control<br>Appliance<br>Clock<br>CO Alarm<br>CO2 Alarm<br>Emergency Alarm<br>Heat Alarm<br>Home Health<br>Home Security<br>Power Management<br>Smoke Alarm<br>System<br>Water Alarm |
| <b>Controller Supports Multiple Networks</b>          | Yes  |
| <b>Controller Supports Multiple Z-Wave Interfaces</b> | Yes  |
| <b>Gateway Has Preferred Partners</b>                 | No   |
| <b>Sensors</b>  | Air Temperature<br>Carbon Dioxide  |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## HomeSeer HS3 Home Automation Software

### Z-Wave Product Information

|                                      |     |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology?  | Yes |
| Supports Z-Wave Network Security?    | Yes |
| Supports Z-Wave AES-128 Security S0? | No  |
| Supports Security S2?                | No  |
| SmartStart Compatible?               | No  |

### Z-Wave Technical Information

|  |  |
|--|--|
| <b>Z-Wave Frequency:</b>               | Any (Software)                                 |
| <b>Z-Wave Product ID:</b>              | 0x0003   |
| <b>Z-Wave Product Type:</b>            | 0x0001   |
| <b>Z-Wave Hardware Platform:</b>       | Software                                       |
| <b>Z-Wave Development Kit Version:</b> | 6.51.06  |
| <b>Z-Wave Library Type:</b>            | Static Controller                              |
| <b>Z-Wave Device Type / Role Type:</b> | Central Controller / Central Static Controller |

### Association Group Information

| Group # / Max | Description          |
|---------------|----------------------|
| <b>Nodes</b>  |                      |
| 1 / 230       | Z-Wave Plus Lifeline |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## HomeSeer HS3 Home Automation Software

### Controlled Command Classes (44):

|                                  |                              |
|----------------------------------|------------------------------|
| Association Group Information V1 | Association V2               |
| Barrier Operator                 | Basic                        |
| Battery                          | Clock                        |
| Configuration                    | Controller Replication       |
| CRC16 Encapsulation              | Device Reset Locally         |
| Door Lock                        | Door Lock Logging            |
| Firmware Update Meta-Data V2     | Indicator                    |
| Manufacturer Specific            | Meter Pulse                  |
| Meter V4                         | Multi Channel Association V2 |
| Multi-Channel V4                 | No Operation                 |
| Node Naming                      | Notification V5              |
| Protection                       | Scene Activation             |
| Scene Actuator Conf              | Scene Controller Conf        |
| Security S0                      | Sensor Multilevel            |
| Sensor Multilevel V7             | Switch All                   |
| Switch Binary                    | Switch Color                 |
| Thermostat Fan Mode V4           | Thermostat Fan State V2      |
| Thermostat Mode V2               | Thermostat Operating State   |
| Thermostat Setback               | Thermostat Setpoint V3       |
| Time Parameters                  | Time V2                      |
| User Code                        | Version V2                   |
| Wake Up V2                       | Z-Wave Plus Info V2          |