

## Z-Wave Protocol Implementation Conformance Statement

### Smart Plug in Switch

#### General Information

<b>Product Identifier:</b>	TZ68E
<b>Brand Name:</b>	TKB Home
<b>Product Version:</b>	01
<b>Z-Wave Certification #:</b>	ZC10-15100001

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0004
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
1 / 1	Z-Wave Plus Lifeline The Switch can be set to send reports to control associated Z-Wave devices. It supports one association group with one node support for Grouping 1. For group 1, the Switch will report its latest status to Z-Wave Controller. Grouping 1 includes, SWITCH_BINARY_REPORT, ALARM_REPORT