

## Z-Wave Protocol Implementation Conformance Statement

### Door/ Window Sensor Gen5

#### General Information

<b>Product Identifier:</b>	ZW120-C
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 78 FW: 1.05
<b>Z-Wave Certification #:</b>	ZC10-15120008

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0078
<b>Z-Wave Product Type:</b>	0x002
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                      Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. The sensor binary report, basic set or notification report command can be sent in this group when the Sensor is triggered.

**Controlled Command Classes (1):**

Basic