

Z-Wave Protocol Implementation Conformance Statement

Door/ Window Sensor

General Information

Product Identifier:	FT112-A
Brand Name:	Oomi
Product Version:	HW: 112 FW: 1.01
Z-Wave Certification #:	ZC10-16015010

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0070
Z-Wave Product Type:	0x0102
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. The sensor binary report, basic set or notification report command can be sent in this group when the Sensor is triggered.

Controlled Command Classes (1):

Basic