

Z-Wave Protocol Implementation Conformance Statement

Smart Energy plug In switch

General Information

Product Identifier:	PAN15-1-NES
Brand Name:	Philio
Product Version:	HW: 1 FW: 1.04
Z-Wave Certification #:	ZC10-16045031

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0038
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 1	Z-Wave Plus Lifeline The Switch can be set to send reports to associated Z-Wave devices. It supports one association group with one node support for Grouping 1. For group 1, the Switch will report its latest status to Z-Wave Controller. Grouping 1 includes, SWITCH_BINARY_REPORT, ALARM_REPORT.