

Z-Wave Protocol Implementation Conformance Statement

FIBARO Wall Plug E/F

General Information

Product Identifier:	FGWPE/F-102
Brand Name:	FIBARO
Product Version:	HW: 2 FW: 3.15:03.02
Z-Wave Certification #:	ZC10-16035016

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1001
Z-Wave Product Type:	0x0602
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 10	“On/Off (button)” devices in this group will be switched on or off when relay status is changed using the B-button (done via BASIC SET command frames).
3 / 10	“On/Off (power)” devices in this group will be switched on or off depending on the current load (done via BASIC SET command frames).

Controlled Command Classes (2):

Basic

Multi-Channel V4