



## Z-Wave Protocol Implementation Conformance Statement

# Smart Home Controller

### General Information

<b>Product Identifier:</b>	VeraEdge-US
<b>Brand Name:</b>	Vera Control, Ltd.
<b>Product Version:</b>	HW: 4 FW: 4.05.03.07
<b>Z-Wave Certification #:</b>	ZC10-16095226

### Product Features

<b>Communications Protocol</b>	Z-Wave Serial API
<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Color</b>	Black
<b>Communications Connections</b>	Ethernet (Wired) Ethernet (Wireless/WiFi) USB (Universal Serial Bus)

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0023
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Home Controller

### Association Group Information

**Group # / Max    Description**

**Nodes**

**Controlled Command Classes (40):**

Alarm V2	Application Status
Association Group Information V1	Association V2
Barrier Operator	Basic
Battery	Central Scene
Climate Control Schedule	Clock
Color Switch V1	Controller Replication
CRC16 Encapsulation	Device Reset Locally
Door Lock V2	Firmware Update Meta-Data V2
Hail	Manufacturer Specific
Meter Pulse	Meter Table Monitor
Meter V2	Multi-Channel Association V3
Multi-Channel V4	Multi-Command
Node Naming	Schedule Entry Lock V3
Security S0	Sensor Alarm
Sensor Binary	Sensor Multilevel V5
Switch Binary	Switch Multilevel V3
Thermostat Fan Mode	Thermostat Mode V2
Thermostat Operating State	Thermostat Setpoint
User Code	Version V2
Wake Up V2	Z-Wave Plus Info V2