



PLUS

Indoor Siren

General Information

Product Identifier: ZSE01
Brand Name: Zooz

Product Version: HW: 2 FW: 0.02 Z-Wave Certification #: ZC10-16045044

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico

Z-Wave Product ID: 0x0003
 Z-Wave Product Type: 0x0003
 Z-Wave Hardware Platform: ZM5202
 Z-Wave Development Kit Version: 6.51.06

Z-Wave Library Type: Routing Slave

Z-Wave Device Type / Role Type: Siren / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline If setting the association this siren may send the Switch_Binary_report to the node.

Supported Command Classes (10):

Association Group Information V1 Command Class Association V2
Command Class Basic Command Class Device Reset Locally

Command Class Manufacturer Specific V2

Command Class Switch All

Command Class Switch Binary

Command Class Version V2

Command Class Z-Wave+ Info V2