

## Z-Wave Protocol Implementation Conformance Statement

### IN-Wall Smart Meter TR Duplex Receptacle

#### General Information

<b>Product Identifier:</b>	ZW15RM
<b>Brand Name:</b>	Enerwave Green Automation
<b>Product Version:</b>	HW: 1 FW: 5.10
<b>Z-Wave Certification #:</b>	ZC10-16055066

#### Product Features

<b>Supported Meter Type</b>	Electric Energy
<b>Switch Type</b>	Push Button with Indicator

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0105
<b>Z-Wave Product Type:</b>	0x0111
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	Lifeline: Send device reset locally notification
2 / 5	StatusReport: Send basic report

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## IN-Wall Smart Meter TR Duplex Receptacle