



## Z-Wave Protocol Implementation Conformance Statement

### Z-Uno

#### General Information

**Product Identifier:** v3  
**Brand Name:** Z-Wave.Me  
**Product Version:** HW: 1 FW: 0.70  
**Z-Wave Certification #:** ZC10-16065104

#### Product Features

**Communications Connections** USB (Universal Serial Bus)

**Firmware Updatable** Updatable by Consumer by Wire

**Sensors**

- Air Temperature
- Carbon Dioxide
- Carbon Monoxide
- Freeze
- Heat
- Humidity
- Luminance
- Moisture
- Motion/No Motion (Binary)
- Open/Closed (Binary)
- Smoke Density
- Vibration/Shock (Binary)
- Water Flow

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? No  
SmartStart Compatible? No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Uno

### Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0110
Z-Wave Hardware Platform:	WML-C85
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

#### Nodes

1 / 5	Z-Wave Plus Lifeline. All unsolicited reports on all channels are sent to this group
2 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
3 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
4 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
5 / 5	Configurable group to send on/off, dimming or scene activation. See product reference

<b>Controlled Command Classes (4):</b>	iming or scene activation. See product reference
--	--

Basic	Multi-Channel V4
Security S0	Switch Multilevel