

Z-Wave Protocol Implementation Conformance Statement

Scene Controller

General Information

Product Identifier:	HKZW-SCN01
Brand Name:	Hank
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-16085175

Product Features

Battery Quantity	1
Battery Type	LIR2450
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0009
Z-Wave Product Type:	0x0200
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Scene Controller

- 2 / 5 Scene Controller will send Basic Set command to the associated nodes.
- 3 / 5 Scene Controller will send switch multilevel set, the multilevel start level change and multilevel stop level change command to the associated nodes.

Controlled Command Classes (4):

Basic

Battery

Central Scene V2

Switch Multilevel V2