

Z-Wave Protocol Implementation Conformance Statement

Remote Temperature and Humidity Sensor

General Information

Product Identifier:	ZSENS930AW00MAA
Brand Name:	Nexia
Product Version:	2.1.28
Z-Wave Certification #:	ZC10-16105290

Product Features

Battery Type	AAA
Color	White
Firmware Updatable	Updatable by Consumer by RF
Sensors	Air Temperature Humidity
Battery Quantity	2

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x54 3
Z-Wave Product Type:	0x52 5
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Remote Temperature and Humidity Sensor

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	Z-Wave Plus Lifeline: COMMAND_CLASS_BATTERY, BATTERY_REPORT COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT COMMAND_CLASS_DEVICE_RESET_LOCALLY, DEVICE_RESET_LOCALLY_NOTIFICATION
2 / 5	Temperature reports from: COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT
3 / 5	Humidity reports from: COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT
Controlled Command Classes (1):	n: COMMAND_CLASS_BASIC, BASIC_SET
5 / 5 ^{Basic}	COMMAND_CLASS_BASIC, BASIC_SET
6 / 5	BATTERY_REPORT sent when sent to Lifeline: COMMAND_CLASS_BATTERY, BATTERY_REPORT