

Z-Wave Protocol Implementation Conformance Statement

Zooz Z-Wave On / Off Light Switch

General Information

Product Identifier:	ZEN21
Brand Name:	Zooz
Product Version:	HW: 1 FW: 20.15
Z-Wave Certification #:	ZC10-16085193

Product Features

Color	White
Electric Load Type	Fluorescent Incandescent LED
Switch Load Capacity Current	15 Amps
Switch Load Capacity Watts	960 Watts (incandescent); 1800 Watts (resistive)
Neutral Wire Required	Yes
Switch Type	Decorator Paddle Push with Indicator

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Zooz Z-Wave On / Off Light Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x231C
Z-Wave Product Type:	0x0111
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
----------------------	--------------------

Nodes

1 / 5	Depending on your Z-Wave gateway's home automation software capabilities, you may be able to associate your Z-Wave switch in groups with other Z-Wave devices to schedule scenes and create events. This on off switch supports Group 1 with up to five devices for lifeline communication. This device will send SWITCH BINARY REPORT to Group 1 when operated manually. Please refer to your controller's user guide for advanced programming instructions as they are a little different for every software.
-------	---