



## Z-Wave Protocol Implementation Conformance Statement

### nexTouch Wireless Push Button with Z-Wave

#### General Information

<b>Product Identifier:</b>	NTB610-ZW2
<b>Brand Name:</b>	Yale Locks & Hardware
<b>Product Version:</b>	HW: 255 FW: 1.67:15.00
<b>Z-Wave Certification #:</b>	ZC10-16095224

#### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	AA
<b>Color</b>	Chrome
<b>Door Lock Type</b>	Lever Handle
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>IP (Ingress Protection) Rated</b>	Yes
<b>Outdoor Use</b>	Yes

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## nexTouch Wireless Push Button with Z-Wave

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0B00
<b>Z-Wave Product Type:</b>	0x8001
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                Z-Wave Plus Lifeline

**Supported Command Classes (18):**

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Door Lock Logging
Door Lock V2	Firmware Update Meta-Data V3
Manufacturer Specific V2	Notification V4
Powerlevel	Schedule Entry Lock V3
Security S0	Time Parameters
Time V2	User Code
Version V2	Z-Wave Plus Info V2