

Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Motion Switch

General Information

Product Identifier:	26931/ZW4006
Brand Name:	GE
Product Version:	HW: 255 FW: 5.56
Z-Wave Certification #:	ZC10-16105294

Product Features

Firmware Updatable	Updatable by Consumer by RF
Sensors	Motion/No Motion (Binary)
Neutral Wire Required	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3032
Z-Wave Product Type:	0x494D
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Motion Switch

- 2 / 5 Supports Basic Set and is controlled with the local load.
- 3 / 5 Supports Basic Set and is controlled by pressing the On or Off buttons.

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic