



PLUS

In-Wall Smart Toggle Switch (Lt. Almond)

General Information

Product Identifier: 14320/ZW4003

Brand Name: Jasco Products Company

Product Version: HW: 255 FW: 5.20 Z-Wave Certification #: ZC10-16115299

Product Features

Firmware Updatable Updatable Updatable by Consumer by RF

Neutral Wire Required Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico

Z-Wave Product ID: 0x3132
 Z-Wave Product Type: 0x4952
 Z-Wave Hardware Platform: ZM5202
 Z-Wave Development Kit Version: 6.51.06

Z-Wave Library Type: Enhanced 232 Slave

Z-Wave Device Type / Role Type: On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline, Binary Switch Report.

2 / 5 Supports Basic Set and is controlled with the local load.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Toggle Switch (Lt. Almond)

Supported Command Classes (15):

Association Group Info

Basic

CRC16 Encapsulation

Firmware Update Meta-Data V2

Powerlevel

Scene Actuator Conf

Switch Binary

Z-Wave Plus Info V2

Association V2 Configuration

Device Reset Locally Manufacturer Specific V2

Scene Activation

Switch All

Version V2

Controlled Command Classes (1):

Basic