

Z-Wave Protocol Implementation Conformance Statement

Samsung SmartThings Hub

General Information

Product Identifier:	STH-ETH-250
Brand Name:	SmartThings
Product Version:	HW: 6 FW: 3.83:00.14
Z-Wave Certification #:	ZC10-16115320

Product Features

Gateway Has Preferred Partners	Yes
Communications Connections	Ethernet (Wired)
Communications Protocol	Z-Wave Serial API
Controller Supports Multiple Networks	No
Controller Supports Multiple Z-Wave Interfaces	No
Firmware Updatable	Updatable by Consumer by Wire
Z-Wave Scene Type	Central Scene
Battery Quantity	4
Battery Type	AA
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Samsung SmartThings Hub

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x000C
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZM5304
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Static Controller
Z-Wave Device Type / Role Type:	Central Controller / Central Static Controller

Association Group Information

Group # / Max Description

Nodes

1 / 4 Z-Wave Plus Lifeline

Supported Command Classes (11):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
No Operation	Powerlevel
Security S0	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (27):

Association Group Info	Association V2
Barrier Operator	Basic
Battery	Configuration V2
CRC16 Encapsulation	Device Reset Locally
Door Lock V2	Manufacturer Specific V2
Meter V3	Multi-Channel Association V3
Multi-Channel V4	Notification V5
Security S0	Sensor Binary V2
Sensor Multilevel V5	Switch Binary
Switch Color V2	Switch Multilevel V3
Thermostat Fan Mode V3	Thermostat Mode V2
Thermostat Operating State V2	Thermostat Setpoint V2
Version V2	Wake Up V2
Z-Wave Plus Info V2	