

Z-Wave Protocol Implementation Conformance Statement

Strips-MaZw

General Information

Product Identifier: 11 01 012
Brand Name: Sensative
Product Version: HW: 2 FW: 10.07:10.08
Z-Wave Certification #: ZC10-16115328

Product Features

Sensors Open/Closed (Binary)
Color White
Outdoor Use Yes
Battery Quantity 1
Battery Type Built in 3.0V LiMnO2

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x0003
Z-Wave Product Type: 0x0003
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.51.06
Z-Wave Library Type: Routing Slave
Z-Wave Device Type / Role Type: Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Strips-MaZw

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Z-Wave Plus Lifeline

Supported Command Classes (12):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Manufacturer Specific
Notification V4	Powerlevel
Sensor Binary	Version V2
Wake Up V2	Z-Wave Plus Info V2