

Z-Wave Protocol Implementation Conformance Statement

Secure Key Chain Controller

General Information

Product Identifier:	POPE009204
Brand Name:	Popp
Product Version:	HW: 1 FW: 1.01
Z-Wave Certification #:	ZC10-16125340

Product Features

Battery Quantity	1
Battery Type	CR2032
Color	Black
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0301
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.03
Z-Wave Library Type:	Portable Controller
Z-Wave Device Type / Role Type:	Remote Control - Simple / Portable Controller

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Secure Key Chain Controller

- 2 / 10 Control Group A, controlled by button 1 or single clicks of buttons 1 and 3
- 3 / 10 Control Group B, controlled by button 2 or single clicks of buttons 2 and 4
- 4 / 10 Control Group C, controlled by button 3 or double clicks of buttons 1 and 3
- 5 / 10 Control Group D, controlled by button 4 or double clicks of buttons 2 and 4

Supported Command Classes (16):

- | | |
|------------------------|------------------------------|
| Association Group Info | Association V2 |
| Battery | Central Scene |
| Configuration | Device Reset Locally |
| Manufacturer Specific | Multi Channel Association V2 |
| Multi-Command | Powerlevel |
| Scene Controller Conf | Security S0 |
| Switch Multilevel | Version V2 |
| Wake Up V2 | Z-Wave Plus Info V2 |

Controlled Command Classes (7):

- | | |
|---------------|------------------|
| Basic | Central Scene |
| Door Lock | Multi-Channel V4 |
| Multi-Command | Security S0 |
| Wake Up V2 | |