



# **PLUS**

# WS15Z5-1

### **General Information**

Product Identifier: WS15Z5-1
Brand Name: GoControl

Product Version: HW: 255 FW: 1.26 Z-Wave Certification #: ZC10-17045537

# **Product Features**

Electric Load Type Incandescent

Neutral Wire Required Yes

Switch Load Capacity Volt-Ampere 15

Z-Wave Scene Type Central Scene

**Color** White

# **Z-Wave Product Information**

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

### **Z-Wave Technical Information**

**Z-Wave Frequency:** U.S. / Canada / Mexico

Z-Wave Product ID: 0x3535
 Z-Wave Product Type: 0x5753
 Z-Wave Hardware Platform: ZM5202
 Z-Wave Development Kit Version: 6.51.09

**Z-Wave Library Type:** Enhanced 232 Slave

**Z-Wave Device Type / Role Type:** On/Off Power Switch / Always On Slave

# **Z-Wave Protocol Implementation Conformance Statement**

# (Continued)

WS15Z5-1

# **Association Group Information**

Group # / Max Description

**Nodes** 

1 / 5 Z-Wave Plus Lifeline

2/5 Other Non-Dimming devices

3/5 Dimmers

### **Supported Command Classes (15):**

Association Group Info

Basic V2

Configuration V3

Firmware Update Meta-Data V2

Powerlevel

Scene Actuator Conf

Switch Binary

Z-Wave Plus Info V2

Association V2 Central Scene V2 Device Reset Locally Manufacturer Specific V2

Scene Activation

Switch All Version V2

# **Controlled Command Classes (1):**

Basic V2