



Z-Wave Protocol Implementation Conformance Statement

Z-Wave Plus Single Gang Decora Wireless Light Switch

General Information

Product Identifier:	DLS-ZWAVE5
Brand Name:	Ecolink Intelligent Technology
Product Version:	HW: 255 FW: 10.01
Z-Wave Certification #:	ZC10-17025449

Product Features

Color	White
Battery Quantity	2
Battery Type	AA, Alkaline
Switch Type	Decorator Paddle Push
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0006
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Listening Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Plus Single Gang Decora Wireless Light Switch

Association Group Information

Group # / Max **Description**

Nodes

2 / 5 Z-Wave Plus Lifeline

Supported Command Classes (10):

Association Group Info	Association V2
Basic	Battery
Device Reset Locally	Manufacturer Specific
Powerlevel	Switch Binary
Version V2	Z-Wave Plus Info V2