

Z-Wave Protocol Implementation Conformance Statement

Ceiling Mounted PIR Motion Sensor

General Information

Product Identifier:	ZWN-BPC
Brand Name:	Enerwave Green Automation
Product Version:	HW: 1 FW: 5.10
Z-Wave Certification #:	ZC10-17015395

Product Features

Battery Quantity	2
Battery Type	AA
Sensors	Motion/No Motion (Binary)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0901
Z-Wave Product Type:	0x0601
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Routing Slave, No FLIRS, No MR
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Ceiling Mounted PIR Motion Sensor

2 / 5 Sensor Basic rep: Basic Report
3 / 5 Sensor Notifi rep: Notification Report
4 / 5 Sensor Basic set: Basic Set 0x00/0xFF

Supported Command Classes (11):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Manufacturer Specific V2
Notification V4	Powerlevel
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic