

Z-Wave Protocol Implementation Conformance Statement

In-Wall On/Off Switch Module

General Information

Product Identifier:	LIZY0005
Brand Name:	COMAP
Product Version:	HW: 2 FW: 1.02:00.01
Z-Wave Certification #:	ZC10-17025432

Product Features

Gateway Has Preferred Partners	Yes
Switch Load Capacity Watts	2500W
Loads Controlled	2
Supported Notification Types	System
Switch Type	Push Button
Color	White
Communications Protocol	Z-Wave Serial API
Electric Load Type	Incandescent LED
Firmware Updatable	Not Updatable

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall On/Off Switch Module

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0008
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.51.02
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1	Lifeline frame : groupingIdentifier + maxNodesSupported + reportsToFollow + nodeid1
2 / 4	On/Off control (Button1) frame : groupingIdentifier + maxNodesSupported + reportsToFollow + nodeid1 + nodeid2 + nodeid3 + nodeid4

Supported Command Classes (13):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Switch All
Switch Binary	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic