

Z-Wave Protocol Implementation Conformance Statement

WallMote

General Information

Product Identifier:	ZW129-A
Brand Name:	Aeotec
Product Version:	HW: 129 FW: 1.05
Z-Wave Certification #:	ZC10-17025439

Product Features

Firmware Updatable	Updatable by Consumer by RF
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0081
Z-Wave Product Type:	0x0102
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.61.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	Z-Wave Plus Lifeline. When touching the Button 1 to 2, the Central Scene Notification command will be sent to the associated node (1) in Association group 1.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

WallMote

- 3 / 5 When touching the Button 1, the Multilevel Switch Set command will be sent to the associated nodes in Association group 3.
- 4 / 5 When touching the Button 2, the Basic Set command will be sent to the associated nodes in Association group 4.
- 5 / 5 When touching the Button 2, the Multilevel Switch Set command will be sent to the associated nodes in Association group 5.

Supported Command Classes (16):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Security S0	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (3):

Basic	Switch Binary V2
Switch Multilevel V4	