

Z-Wave Protocol Implementation Conformance Statement

Smart Dimmer 6

General Information

Product Identifier:	ZW099-A02
Brand Name:	Aeotec
Product Version:	HW: 99 FW: 1.11
Z-Wave Certification #:	ZC10-17035455

Product Features

Switch Load Capacity Current	2.5A
Z-Wave Scene Type	Scene
Firmware Updatable	Updatable by Consumer by RF
Color	White
Electric Load Type	Dimmable LED Incandescent
Supported Meter Type	Electric Energy

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0063
Z-Wave Product Type:	0x0103
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Dimmer 6

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline The Basic Report CC and Hail CC (configured by parameter 80) can be sent to this association group.

2 / 5 The Basic Set and Switch Multilevel CC will be sent to the associated nodes in this group when the Smart Dimmer 6 receives the Basic Set or Switch Multilevel CC from the main controller.

Supported Command Classes (20):

Association Group Info	Association V2
Basic	Clock
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Meter V3	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Switch All
Switch Color	Switch Multilevel V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Basic	Hail
-------	------