

Z-Wave Protocol Implementation Conformance Statement

DIN Dimmer

General Information

Product Identifier:	ZMNHSD1
Brand Name:	QUBINO
Product Version:	HW: 2 FW: 2.02:02.02
Z-Wave Certification #:	ZC10-17035480

Product Features

Switch Type	Push Button
Color	Light Blue
Sensors	Air Temperature

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0052
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

DIN Dimmer

- 2 / 16 Basic on/off (triggered at change of the input I1 state and reflecting its state)
- 3 / 16 Start level change/stop level change (triggered at change of the input I1 state and reflecting its state)
- 4 / 16 Multilevel set (triggered at changes of state/value of the DIN Dimmer)
- 5 / 16 Multilevel sensor report (triggered at change of temperature sensor)

Supported Command Classes (17):

Association Group Information V2	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Security S0	Sensor Multilevel V7
Switch All	Switch Binary
Switch Multilevel V3	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Basic	Switch Multilevel V3
-------	----------------------