

Z-Wave Protocol Implementation Conformance Statement

ID Lock 101

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | ID-101 |
| Brand Name: | ID Lock |
| Product Version: | HW: 1 FW: 1.00 |
| Z-Wave Certification #: | ZC10-17055585 |

Product Features

| | |
|--------------------------------------|--|
| Door Lock Type | Deadbolt Motor Attachment |
| Firmware Updatable | Updatable by Consumer by RF |
| IP (Ingress Protection) Rated | Yes |
| Outdoor Use | Yes |
| Sensors | Air Temperature Open/Closed (Binary) RF Signal Strength Voltage |
| Supported Notification Types | Access Control |
| Battery Quantity | 4x or 8x |
| Battery Type | AA |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

ID Lock 101

Z-Wave Technical Information

| | |
|--|---|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0001 |
| Z-Wave Product Type: | 0x0030 |
| Z-Wave Hardware Platform: | ZM5202 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Door Lock - Keypad / Listening Sleeping Slave |

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (14):

| | |
|------------------------------|--------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Door Lock V2 |
| Firmware Update Meta-Data V2 | Manufacturer Specific V2 |
| Notification V4 | Powerlevel |
| Security S0 | User Code |
| Version V2 | Z-Wave Plus Info V2 |