

Z-Wave Protocol Implementation Conformance Statement

Smart Plug switch

General Information

Product Identifier:	ZW36
Brand Name:	EVA LOGIK
Product Version:	HW: 0 FW: 20.15
Z-Wave Certification #:	ZC10-17045547

Product Features

Electric Load Type	Fluorescent Incandescent LED
Firmware Updatable	Not Updatable
IP (Ingress Protection) Rated	No
Neutral Wire Required	Yes
Switch Load Capacity Watts	1200
Switch Type	Push Button
Switch Load Capacity Current	10
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x241C
Z-Wave Product Type:	0xB211
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (9):

Association Group Info	Association V2
Basic	Device Reset Locally
Manufacturer Specific V2	Powerlevel
Switch Binary	Version V2
Z-Wave Plus Info V2	