

Z-Wave Protocol Implementation Conformance Statement

Cube

General Information

| | |
|--------------------------------|------------------------|
| Product Identifier: | FT101-B |
| Brand Name: | Oomi |
| Product Version: | HW: 101 FW: 1.02:01.01 |
| Z-Wave Certification #: | ZC10-17055599 |

Product Features

| | |
|-------------------------------------|-------------------------------------------------------------------------------------|
| Communications Connections | Bluetooth Ethernet (Wired) Ethernet (Wireless/WiFi) |
| Communications Protocol | Manufacturer Proprietary Protocol |
| Firmware Updatable | Updatable by Consumer via Internet |
| Sensors | Air Temperature Current Humidity Luminance Ultraviolet Index Voltage |
| Supported Notification Types | Clock Home Security System Water Alarm |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Cube

Z-Wave Technical Information

| | |
|----------------------------------------|-------------------------------------|
| Z-Wave Frequency: | Australia / New Zealand |
| Z-Wave Product ID: | 0x0065 |
| Z-Wave Product Type: | 0x0201 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.09 |
| Z-Wave Library Type: | Static Controller |
| Z-Wave Device Type / Role Type: | Gateway / Central Static Controller |

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline. The Device Reset Locally CC will be sent to the associated nodes in this group when the Cube is reset.

Supported Command Classes (10):

| | |
|----------------------|--------------------------|
| Application Status | Association Group Info |
| Association V2 | CRC16 Encapsulation |
| Device Reset Locally | Manufacturer Specific V2 |
| Powerlevel | Security S0 |
| Version V2 | Z-Wave Plus Info V2 |

Controlled Command Classes (27):

| | |
|------------------------------|------------------------|
| Association Group Info | Association V2 |
| Basic | Battery |
| Clock | Configuration |
| Controller Replication | CRC16 Encapsulation |
| Hail | Meter V3 |
| Multi-Channel Association V3 | Multi-Channel V4 |
| Notification V4 | Powerlevel |
| Security S0 | Sensor Binary |
| Sensor Multilevel V5 | Switch Binary |
| Switch Color | Switch Multilevel V2 |
| Thermostat Fan State | Thermostat Mode V2 |
| Thermostat Operating State | Thermostat Setpoint V2 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |