

Z-Wave Protocol Implementation Conformance Statement

Smart energy plug-in switch

General Information

Product Identifier:	ph-pan16.eu
Brand Name:	Zipato
Product Version:	HW: 1 FW: 1.03
Z-Wave Certification #:	ZC10-17055605

Product Features

Electric Load Type	Incandescent
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	13A
Supported Meter Type	Electric Energy
Color	White
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0029
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart energy plug-in switch

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Lifeline The Switch can be set to send reports to associated Z-Wave devices. It supports one association group with one node support for Grouping 1. For group 1, the Switch will report its latest status to Z-Wave Controller. Grouping 1 includes, SWITCH_BINARY_REPORT, METER_REPORT, ALARM_REPORT.

Supported Command Classes (16):

Alarm	Association Group Info
Association V2	Basic
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific
Meter V3	Powerlevel
Protection V2	Security S0
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2