

Z-Wave Protocol Implementation Conformance Statement

Smoke Sensor, Z-Wave

General Information

Product Identifier:	ph-psg01.eu
Brand Name:	Zipato
Product Version:	HW: 1 FW: 1.23:01.24
Z-Wave Certification #:	ZC10-17055607

Product Features

Battery Quantity	1
Color	White
Supported Notification Types	Home Security Smoke Alarm
Battery Type	CR123A

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x001E
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.51.02
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smoke Sensor, Z-Wave

Association Group Information

Group # / Max **Description**

Nodes

1 / 8 Z-Wave Plus Lifeline

Supported Command Classes (14):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Sensor Binary V2	Version V2
Wake Up V2	Z-Wave Plus Info V2