

Z-Wave Protocol Implementation Conformance Statement

Siren

General Information

Product Identifier:	SIR-01
Brand Name:	LG U+
Product Version:	HW: 18 FW: 39.36
Z-Wave Certification #:	ZC10-17065638

Product Features

Firmware Updatable	Updatable by Professional/Technician
Battery Quantity	2
Color	White
Switch Type	Push Button
Battery Type	AA Battery
IP (Ingress Protection) Rated	No
Outdoor Use	No
Supported Notification Types	Emergency Alarm Home Security

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Siren

Z-Wave Technical Information

Z-Wave Frequency:	South Korea
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x004E
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.61.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Siren / Listening Sleeping Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Lifeline Association Group supporting up to 5 nodes.

Supported Command Classes (14):

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific
Notification V3	Powerlevel
Security S0	Switch Binary
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Configuration	Switch Binary
---------------	---------------