

Z-Wave Protocol Implementation Conformance Statement

AC MASTER

General Information

Product Identifier:	ZXT-600US
Brand Name:	Remotec
Product Version:	HW: 3 FW: 0.21:00.32:171.01
Z-Wave Certification #:	ZC10-17055619

Product Features

Thermostat Modes	Auto Away Cool Dry Air Fan Only Heat Resume
Firmware Updatable	Updatable by Consumer by RF
Battery Type	AA x 2
Color	White
Sensors	Target Temperature

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

AC MASTER

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x8490
Z-Wave Product Type:	0x0100
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.61.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Thermostat - HVAC / Listening Sleeping Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	Association Group #1 (max. 1 node) is default to associate with the primary controller (Gateway/Hub/Controller) for AC Master Status change report, refer to below for report details: a) Current Room Temperature (report in precision of 0.5°C or 1°F) (It will be according to Configuration Parameter 39 setting to decide the trigger level) b) Current Battery Level (Only apply in Low Battery Warning happened) c) Device Reset Locally Notification (Only report when the AC Master has been triggered the RESET TO DEFAULT)
-------	---

Supported Command Classes (16):

Application Status	Association Group Information V3
Association V2	Basic
Battery	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific V2
Powerlevel	Security S0
Sensor Multilevel V7	Thermostat Fan Mode V4
Thermostat Mode V3	Thermostat Setpoint V3
Version V2	Z-Wave Plus Info V2