

Z-Wave Protocol Implementation Conformance Statement

Smart Plug Switch (2 channel)

General Information

Product Identifier:	ZW37
Brand Name:	EVA LOGIK
Product Version:	HW: 0 FW: 20.15
Z-Wave Certification #:	ZC10-17065636

Product Features

Color	White
Electric Load Type	Fluorescent Incandescent Inductive (e.g. Motor) LED
Firmware Updatable	Not Updatable
Switch Load Capacity Current	15
Switch Load Capacity Volt-Ampere	120
Switch Load Capacity Watts	1800

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug Switch (2 channel)

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x241C
Z-Wave Product Type:	0xB211
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 2 Z-Wave Plus Lifeline

Supported Command Classes (11):

Association Group Info	Association V2
Basic	Device Reset Locally
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Switch Binary	Version V2
Z-Wave Plus Info V2	