

Z-Wave Protocol Implementation Conformance Statement

4in1 PIR Sensor

General Information

Product Identifier:	ZP3111JP-5
Brand Name:	Vision
Product Version:	HW: 5 FW: 5.01:10.01
Z-Wave Certification #:	ZC10-17075680

Product Features

Supported Notification Types	Access Control
Battery Type	AAA
Color	White
Communications Protocol	Z-Wave Z/IP
Firmware Updatable	Updatable by Consumer by RF
Sensors	Motion/No Motion (Binary)
Battery Quantity	2

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

4in1 PIR Sensor

Z-Wave Technical Information

Z-Wave Frequency:	Japan
Z-Wave Product ID:	0x2101
Z-Wave Product Type:	0x2021
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Lifeline COMMAND_CLASS_BASIC_SET COMMAND_CLASS_BATTERY_REPORT
 COMMAND_CLASS_DEVICE_RESET_LOCALLY_NOTIFICATION

Supported Command Classes (14):

_REPORT COMMAND_CLASS_SENSOR_MULTILEVEL_V7

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Sensor Multilevel V7	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic