

Z-Wave Protocol Implementation Conformance Statement

WO15EMZ5-1

General Information

Product Identifier:	WO15EMZ5-1
Brand Name:	GoControl
Product Version:	HW: 1 FW: 1.35
Z-Wave Certification #:	ZC10-17075714

Product Features

Supported Meter Type	Electric Energy
Switch Type	Push Button with Indicator
Color	White
Electric Load Type	ELV (Electronic) Fluorescent Incandescent LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	15
Neutral Wire Required	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

WO15EMZ5-1

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3535
Z-Wave Product Type:	0x574F
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.10
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (16):

Association Group Info	Association V2
Basic	Basic V2
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Meter V4	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2