

Z-Wave Protocol Implementation Conformance Statement

In-Wall On/Off Switch

General Information

Product Identifier:	HS-WS100+
Brand Name:	HomeSeer
Product Version:	HW: 255 FW: 5.16
Z-Wave Certification #:	ZC10-17085737

Product Features

Color	White
Electric Load Type	ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	15 Amps
Switch Load Capacity Watts	900 Watts Incandescent
Neutral Wire Required	Yes
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall On/Off Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3033
Z-Wave Product Type:	0x4447
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (15):

Association Group Info	Association V2
Basic	Central Scene V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Binary	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Central Scene V2