

## Z-Wave Protocol Implementation Conformance Statement

### R200-CH

#### General Information

<b>Product Identifier:</b>	R200-CH
<b>Brand Name:</b>	GATEMAN
<b>Product Version:</b>	HW: 32 FW: 32.16:16.16
<b>Z-Wave Certification #:</b>	ZC10-17085751

#### Product Features

<b>Color</b>	Black
<b>Battery Quantity</b>	4
<b>Communications Connections</b>	Bluetooth Manufacturer Proprietary
<b>Door Lock Type</b>	Lever Handle
<b>Gateway Has Preferred Partners</b>	Yes
<b>Battery Type</b>	AA
<b>Supported Notification Types</b>	Access Control Emergency Alarm Home Security Power Management

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

R200-CH

## Z-Wave Technical Information

**Z-Wave Frequency:** South Korea  
**Z-Wave Product ID:** 0x0001  
**Z-Wave Product Type:** 0xC601  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.71.01  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Door Lock - Keypad / Listening Sleeping Slave

## Association Group Information

**Group # / Max Description**

### Nodes

1 / 5 Z-Wave Plus Lifeline

### Supported Command Classes (15):

Alarm	Association Group Info
Association V2	Battery
Device Reset Locally	Door Lock V2
Manufacturer Specific V2	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
User Code	Version V2
Z-Wave Plus Info V2	