



Z-Wave Protocol Implementation Conformance Statement

R200-CH

General Information

Product Identifier:	R200-CH
Brand Name:	GATEMAN
Product Version:	HW: 32 FW: 32.16:16.16
Z-Wave Certification #:	ZC10-17085751

Product Features

Communications Connections	Bluetooth Manufacturer Proprietary
Supported Notification Types	Access Control Emergency Alarm Home Security Power Management
Gateway Has Preferred Partners	Yes
Door Lock Type	Lever Handle
Battery Type	AA
Battery Quantity	4
Color	Black

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

R200-CH

Z-Wave Technical Information

Z-Wave Frequency:	South Korea
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0xC601
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Door Lock - Keypad / Listening Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (15):

Alarm	Association Group Info
Association V2	Battery
Device Reset Locally	Door Lock V2
Manufacturer Specific V2	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
User Code	Version V2
Z-Wave Plus Info V2	