

Z-Wave Protocol Implementation Conformance Statement

Outlet

General Information

Product Identifier:	WK-0003
Brand Name:	WINKA SYSIT
Product Version:	HW: 16 FW: 1.36
Z-Wave Certification #:	ZC10-17105819

Product Features

Supported Meter Type	Electric Energy
Supported Notification Types	Power Management
Switch Type	Toggle

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1D61
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Outlet

- 2 / 5 Control Group, If over-load is occurred, the device will send BASIC_SET to nodes associated in group 2.
Support Command List as Below: COMMAND_CLASS_BASIC, BASIC_SET
- 3 / 5 Power Manager Group. If Over-load is occurred, device will send notification report to nodes associated in group 3. Support List as Below: COMMAND_CLASS_NOTIFICATION, POWERMANAGEMENT STATUS (OVER LOAD)

Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V4	Notification V8
Powerlevel	Security S0
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic